


Using Presets optimized for ULTIMATE EARS In-Ear Monitors

Follow the steps below to quickly recall an EQ Preset optimized for ULTIMATE EARS In-Ear Monitors. The supported models are as follows.

UE 18 PRO / UE 11 PRO / UE 7 PRO / UE 5 PRO / UE 4 PRO / UE 900S / UE RM
FitEar 334 / FitEar 335 / Yamaha EPH-100

1. Copy the file "EQ_Preset_for_CLQL.CLF" to the root directory of a USB memory and plug it into the CL/QL USB connector.
2. Press and select "EQ_Preset_for_CLQL.CLF" in the file list, or rotate the corresponding multifunction knob on the panel to select it.
3. Press the LOAD button to access the LOAD SELECT popup window.



4. In the SOURCE field, add a check mark (☑) to select the data that you want to Load.



5. In the DESTINATION field, add a check mark (☑) to the load-destination.



NOTE

Please be careful not to mistakenly overwrite the existing library items on the CL/QL console.

6. Press the LOAD button.
7. Select an output channel for which you want to apply the settings, and press the EQ field.



8. Press the LIBRARY tool button to open the corresponding library window.



9. Rotate any of the multifunction knobs to move the highlight line up or down to select the required library item.



10. Press the RECALL button.
11. The selected data will immediately be loaded into the channel you selected in step 7. If necessary, you can further adjust the EQ settings.